Data sheet





quality signal is received outside.

5 bands amplifier

for mobile signals

art. 39-520 T-AMP 5 BANDE 23dBm



MOBILE

Amplifier ideal for the amplification of the mobile phone signal in band 20 (800 MHz), in band 8 (900 MHz), in band 3 (1800 MHz), in band 1 (2100 MHz) and in band 7 (2600 MHz) inside public or private buildings (e.g. houses, restaurants, offices, shops, etc.), where signals are weak or absent, provided that a good



Ideal for amplifying the signal in areas up to 3000÷4000 m².

If you want to spread the signal inside a very large building, you can con with a number of outputs equal to the number of indoor antennas that yo desired signal coverage.

nect to the amplifier a splitter ou need to instal to reach the	CONN. N
	$C \in$

Code		39-520	
Item		T-AMP 5 BANDE 23dBm	
Bands name		Band 20 (800 MHz) Band 8 (900 MHz) Band 3 (1800 MHz) Band 1 (2100 MHz) Band 7 (2600 MHz)	
Band 20 (800 MHz) frequencies	MHz	Uplink: 832 ÷ 862 Downlink: 791 ÷ 821	
Band 8 (900 MHz) frequencies	MHz	Uplink: 880 ÷ 915 Downlink: 925 ÷ 960	
Band 3 (1800 MHz) frequencies	MHz	Uplink: 1715 ÷ 1785 Downlink: 1810 ÷ 1880	
Band 1 (2100 MHz) frequencies	MHz	Uplink: 1920 ÷ 1980 Downlink: 2110 ÷ 2170	
Band 7 (2600 MHz) frequencies	MHz	Uplink: 2510 ÷ 2570 Downlink: 2630 ÷ 2690	
Bandwidth		Band 8: 30 MHz Band 8: 35 MHz Band 3: 70 MHz Band 1: 60 MHz Band 7: 60 MHz	
Max gain	dB	Uplink: ≥70 / Downlink: ≥75	
Max output power	dBm	Uplink: ≥15 / Downlink: ≥23	
Coverage area	m ²	3000 ÷ 4000	

		D0W111111111111111111111111111111111111	
Band 8 (900 MHz) frequencies	MHz	Uplink: 880 ÷ 915 Downlink: 925 ÷ 960	
Band 3 (1800 MHz) frequencies	MHz	Uplink: 1715 ÷ 1785 Downlink: 1810 ÷ 1880	
Band 1 (2100 MHz) frequencies	MHz	Uplink: 1920 ÷ 1980 Downlink: 2110 ÷ 2170	
Band 7 (2600 MHz) frequencies	MHz	Uplink: 2510 ÷ 2570 Downlink: 2630 ÷ 2690	
Bandwidth		Band 8: 30 MHz Band 8: 35 MHz Band 3: 70 MHz Band 1: 60 MHz Band 7: 60 MHz	
Max gain	dB	Uplink: ≥70 / Downlink: ≥75	
Max output power	dBm	Uplink: ≥15 / Downlink: ≥23	
Coverage area	m ²	3000 ÷ 4000	
AGC control range	dB	≥25	
Manual gain adjustment	dB	31 (1 dB per time)	
Max input power	dBm	-27	
Impedance	Ω	50	
Noise figure	dB	≤6	
Group delay time	μs	≤1	
VSWR	dB	≤2	
Spurious emissions 9 kHz - 1 GH	lz	≤-36 dBm	
Spurious emissions 1 GHz - 12.75	5 GHz	≤-30 dBm	
Consumption	W	8	
Connectors		female N type	
Operating temperature	°C	-10 ÷ +50	
Environmental conditions		IP40	
Wall fixing accessory		included	
Dimensions (LxWxH)	mm	373x228x73	
Weight	Kg	9,00	
Packaging dimensions (LxWxH)	mm	450x340x120	
Packaging weight POWER SUPPLY	Kg	9,5	
Power supply	Vdc	10	
Max power consumption	Α	10	
AC main tension		100-240 V~ 50/60Hz	
Isolation class		II	
Dimensions (LxWxH)	mm	170x70x35	
Weight	Kg	0,525	

^{*} The coverage area is an indicative data that changes according to various factors and is different in each system.

In order to obtain the maximum output power of the amplifier (+23 dBm = 130 dB μ V), the input signal to the amplifier must be at least -52 dBm $(55 \text{ dB}\mu\text{V}).$

Characteristics

- Max gain 75 dB with Automatic Gain Adjustment (AGC)
- Detection functions for self-oscillation and overpower
- LED indicators for status, power, alarms
- Compliant to:

2014/53/UE/RED; 2011/65/UE (RoHS) EN 301 489-50 V2.2.1; EN 301 489-1 V2.2.3; EN 301 908-11 V11.1.2; EN 301 908-15 V.11.1.2; EN 303 609 V12.5.1; EN 50385:2017 EN 62368-1: 2014 + A11:2017

Example of application







