# Data sheet





# Dual band amplifier

for mobile signals

# art. 39-514 T-AMP 900/2100 20dBm















Ideal for amplifying the signal in areas up to 500÷2000 m². If you want to spread the signal inside a very large building, you can connect to the amplifier a splitter

Amplifier ideal for the amplification of the mobile phone signal in band 8 (900 MHz) and in band 1 (2100 MHz) inside public or private buildings (e.g. houses, restaurants, offices, shops, etc.), where signals are weak

If you want to spread the signal inside a very large building, you can connect to the amplitier a splitter
with a number of outputs equal to the number of indoor antennas that you need to instal to reach the
desired signal coverage.

Code	Code		39-514	
Item		T-AMP 900/2100 20dBm		
Bands name		Band 8	Band 1	
Bands	MHz	900 MHz	2100 MHz	
Uplink frequencies	MHz	880 ÷ 915	1920 ÷ 1980	
Downlink frequencies	MHz	925 ÷ 960	2110 ÷ 2170	
Bandwidth	MHz	35	60	
Max gain	dB	Uplink: ≥65 / Downlink: ≥70		
Max output power	dBm	Uplink: ≥15 / Downlink: ≥20		
Coverage area	m <sup>2</sup>	500 ÷ 2000		
AGC control range	dB	≥25		
Manual gain adjustment	dB	31 (1 dB per time)		
Max input power	dBm	-25		
Impedance	Ω	50		
Noise figure	dB	≤6		
Group delay time	μs	≤1		
VSWR	dB	≤2		
Spurious emissions 9 kHz - 1 GHz		≤-36 dBm		
Spurious emissions 1 GHz - 12.75 GHz		≤-30 dBm		
Consumption	W	12		
Connectors		female N type		
Operating temperature	°C	-10 ÷ +50		
Environmental conditions		IP40		
Wall fixing accessory	included		ıded	
Dimensions (LxWxH)	mm	128x170x65		
Weight	Kg	2,2		
Packaging dimensions (LxWxH)	mm	440x310x260		
Packaging weight	Kg	2,9		
POWER SUPPLY				
Power supply	Vdc	6		
Max power consumption	Α	3		
AC main tension		100-240 V~ 50/60Hz		
Isolation class		II		
Dimensions (LxWxH)	mm	90x40x50		
Weight	Kg	0,135		

or absent, provided that a good quality signal is received outside.

\* The coverage area is an indicative data that changes according to various factors and is different in each system. In order to obtain the maximum output power of the amplifier (+20 dBm = 127 dB $\mu$ V), the input signal to the amplifier must be at least -50 dBm (57 dB $\mu$ V).


#### **Characteristics**

- Max gain 70 dB with Automatic Gain Adjustment (AGC)
- Detection functions for self-oscillation and overpower
- · LED indicators for status, power, alarms
- Compliant to:

2014/53/UE/RED; 2011/65/UE (RoHS) EN 301 489-50 V2.2.1; EN 301 489-1 V2.2.1; EN 301 908-11 V11.1.2; EN 301 908-11 V11.1.1; EN 301 908-15 V11.1.2; EN 303 609 V12.5.1; EN 60950-1:2006+A11:2009+A1:2010+A12: 2011+A2:2013; EN 50385:2017

### **Example of application**





Rev. 1 07.2025

